



GENERAL CONSTRUCTION NOTE:

1. STANDARD 5/8" SQUARE NUTS ISSUED WITH DA BOLTS, OE BOLTS, MH BOLTS AND STEEL INSULATOR PINS SHOULD BE USED FOR LOCK (JAM) NUTS.
2. DISCARD SQUARE WASHER AND LOCK (MF) NUT ISSUED WITH STEEL INSULATOR PIN, USE ISSUED NUT WASHER IN PLACE OF SQUARE WASHER.

TITLE:

THREE PHASE INLINE  
ON 5' FIBER ARM

**GARLAND**  
POWER & LIGHT

STANDARD NO.:

OH-1605

DRAWN BY: LG	DATE: 3/17/04	APPROVED BY: CP
REVISED BY: JC	DATE: 11/01/05	APPROVED BY:

**CONSTRUCTION STANDARD NO. : OH-1605****TITLE: 3 PHASE INLINE ON 5' FIBER ARM**

REV. DATE: 5/21/2002

PIC. #	DESCRIPTION	IBM NO.	QTY.
1	CROSSARM, 60" x 3" FIBERGLASS (FOR DEAD ENDING CONDUCTORS)	285-21-13755	1
2	PIN POLE TOP, FIBERGLASS, CONTINENTAL GRP-58M-21, 1" THRDS	285-21-13825	1
3	INSULATOR PIN TYPE 15KV	286-42-25100	3
4	PIN STEEL 5/8" X 5-3/4" W/NUTS	285-39-10246	2
5	1 PT RACK GALV 1-1/2" X 1/2" X 1/8" CLEVIS	285-39-14039	1
6	INSULATOR SPOOL TYPE SECONDARY	286-42-23310	1
7	BOLT WASHER HEAD 5/8" X 12" W/ WASHER NUT	285-08-96924	3
8	BOLT WASHER HEAD 5/8" X 14" W/ WASHER NUT	285-08-96926	2